# » LK+ CO2+VOC (LCD) (Temp\_rH) RS485 BACnet

Duct sensor for air quality, optional temperature and humidity



#### **Datasheet**

Subject to technical alteration Issue date: 8/4/2020 • A110





The following illustrations show the version with LCD

#### » APPLICATION

Air quality sensor for measuring VOC air quality, CO2, temperature and humidity in outdoor areas with 2 0..10 V output. LCD models with RGB background light have a transparent cover. Display configuration and threshold values for color changes can be parameterized via Thermokon USEapp.

### »TYPES AVAILABLE

Duct sensor CO2 + VOC + temp + rH (opt.), optional with display - active RS485 BACnet MS/TP

LK+ CO2+VOC (LCD) RS485 BACnet

LK+ CO2+VOC (LCD) Temp RS485 BACnet

LK+ CO2+VOC (LCD) Temp\_rH RS485 BACnet

#### optionally with shorter sensor tube, Type 100

LK+ CO2+VOC (LCD) 100 RS485 BACnet

LK+ CO2+VOC (LCD) 100 Temp RS485 BACnet

LK+ CO2+VOC (LCD) 100 Temp\_rH RS485 BACnet

#### » SECURITY ADVICE - CAUTION



The installation and assembly of electrical equipment should only be performed by authorized personnel.

The product should only be used for the intended application. Unauthorised modifications are prohibited! The product must not be used in relation with any equipment that in case of a failure may threaten, directly or indirectly, human health or life or result in danger to human beings, animals or assets. Ensure all power is disconnected before installing. Do not connect to live/operating equipment.

Please comply with

- Local laws, health & safety regulations, technical standards and regulations
- Condition of the device at the time of installation, to ensure safe installation
- This data sheet and installation manual

Page 2 / 6 Issue date: 8/4/2020

# » NOTES ON DISPOSAL



As a component of a large-scale fixed installation, Thermokon products are intended to be used permanently as part of a building or a structure at a pre-defined and dedicated location, hence the Waste Electrical and Electronic Act (WEEE) is not applicable. However, most of the products may contain valuable materials that should be recycled and not disposed of as domestic waste. Please note the relevant regulations for local disposal.

#### » GENERAL REMARKS CONCERNING SENSORS

Especially with regard to passive sensors in 2-wire conductor versions, the wire resistance of the supply wire has to be considered. If necessary the wire resistance has to be compensated by the follow-up electronics. Due to self-heating, the wire current affects the measurement accuracy, so it should not exceed 1 mA.

When using lengthy connection wires (depending on the cross section used) the measuring result might be falsified due to a voltage drop at the common GND-wire (caused by the voltage current and the line resistance). In this case, 2 GND-wires must be wired to the sensor - one for supply voltage and one for the measuring current.

Sensing devices with a transducer should always be operated in the middle of the measuring range to avoid deviations at the measuring end points. The ambient temperature of the transducer electronics should be kept constant. The transducers must be operated at a constant supply voltage (±0,2 V). When switching the supply voltage on/off, onsite power surges must be avoided.

#### » BUILD-UP OF SELF-HEATING BY ELECTRICAL DISSIPATIVE POWER

Temperature sensors with electronic components always have a dissipative power, which affects the temperature measurement of the ambient air. The dissipation in active temperature sensors shows a linear increase with rising operating voltage. This dissipative power has to be considered when measuring temperature. In case of a fixed operating voltage ( $\pm 0.2 \text{ V}$ ) this is normally done by adding or reducing a constant offset value. As Thermokon transducers work with a variable operating voltage, only one operating voltage can be taken into consideration, for reasons of production engineering. Transducers 0..10 V/4..20 mA have a standard setting at an operating voltage of 24 V = . That means, that at this voltage, the expected measuring error of the output signal will be the least. For other operating voltages, the offset error will be increased by a changing power loss of the sensor electronics. If a re-calibration should become necessary later directly on the sensor, this can be done by means of the USEapp software and an optional Bluetooth interface.

Remark: Occurring draft leads to a better carrying-off of dissipative power at the sensor. Thus temporally limited fluctuations might occur upon temperature measurement.

## » APPLICATION NOTICE FOR HUMIDITY SENSORS

Refrain from touching the sensitive humidity sensor/element. Touching the sensitive surface will void warranty.

For standard environmental conditions re-calibration is recommended once a year to maintain the specified accuracy.

When exposed to high ambient temperature and/or high levels of humidity or presence of aggressive gases (i.e. chlorine, ozone, ammonia) the sensor element may be affected and re-calibration may be required sooner than specified. Re-calibration and deterioration of the humidity sensor due to environmental conditions are not subject of the general warranty.

## » INFORMATION ABOUT INDOOR AIR QUALITY CO2

EN 13779 defines several classes for indoor air quality:

Category	CO <sub>2</sub> content above the content in outdoor air in ppm		Description
	Typical range	Standard value	
IDA1	<400 ppm	350 ppm	Good indoor air quality
IDA2	400 600 ppm	500 ppm	Standard indoor air quality
IDA3	6001.000 ppm	800 ppm	Moderate indoor air quality
IDA4	>1.000 ppm	1.200 ppm	Poor indoor air quality

Issue date: 8/4/2020 Page 3 / 6

#### »INFORMATION ABOUT SELF-CALIBRATION FEATURE CO<sub>2</sub>

All gas sensors are subject to drift caused by components. This fact results generally in the need to recalibrate the sensors regularly.

With dual channel technology Thermokon integrates automatic self-calibration for different fields of operation. In contrast to common used ABC-Logic sensors with self-calibration dual channel are suitable for applications operating 24 hours, 7 days a week as for example hospitals.

Manual calibration is not necessary!

#### » APPLICATION NOTICE FOR AIR QUALITY SENSORS VOC

Unlike  $CO_2$  sensors, which specifically measure  $CO_2$ , mixed gas sensors detect a wide range of gases. The sensor signal does not indicate the type of gas or it's concentration in ppm. Mixed gas sensors detect gases and vapours consisting of carbohydrates, or more generally gases that can be oxidised (burnt): Odours, perfume, cleaning fluid scent, tobacco smoke, new materials fumigations (furniture, carpets, paint, glue ...).

Unlike CO<sub>2</sub>, which humans cannot sense, the amount of odours (VOC) indicates the level of air quality. VOC sensors have proven their value in a multitude of applications for many years.

#### Measuring principle:

Similar to a catalyst converter the organic molecules are burnt (oxidized) when in contact with the sensor's heated -dioxide surface, adding a small amount of heat combustion. The increased temperature is measured providing a signal proportional to the number of molecules being burnt. CO<sub>2</sub> cannot be detected as it cannot be further oxidized.

Refrain from touching the sensor's element sensitive surface. Touching the sensitive surface element will void warranty.

#### »INFORMATION ABOUT CALIBRATION VOC

Similar to a catalyst converter the VOC sensor will deteriorate over time, which will affect the sensitivity. This VOC sensor automatically compensates the decrease in sensitivity by dynamic auto-calibration.

The reference level of air quality is derived from the ambient conditions over a 72h period. The lowest reading within this 72h time period will be used as reference level, representing the "clean and fresh air level".

# » PRODUCT TESTING AND CERTIFICATION



#### **Declaration of conformity**

The declaration of conformity of the products can be found on our website https://www.thermokon.de/.

## » APPLICATION NOTICE



The housing cover must be completely closed in order to ensure the accuracy and reproducibility of the measured values during a test or service log via USEapp.

The Bluetooth dongle snaps into the socket easily. When removing, please fix the plug-in card (option PCB) so that it is not unintentionally pulled out.

#### » CONFIGURATION



The Thermokon bluetooth dongle with micro-USB is required for communication between USEapp and USE-M / USE L (Item No..: 668262). Commercial bluetooth dongles are not compatible.

Application-specific reconfiguration of the devices can be carried out using the Thermokon USEapp. The configuration is carried out in the voltage-supplied state.

The configuration-app and the app description can be found in the Google Play Store or in the Apple App Store.

Page 4 / 6 Issue date: 8/4/2020

# »TECHNICAL DATA

Measuring values (type-dependent)	CO2, VOC, temperature and humidity			
Output voltage	2x 010 V or 05 V, min. load 10 kΩ (live-zero configuration via Thermokon USEapp)			
Network technology	RS485 BACnet MS/TP			
Power supply*	1535 V = or 1929 V ~ SELV  With alternating voltage, the correct polarity must be ensured			
Power consumption	max. 2,3 W (24 V =)   max. 4,3 VA (24 V ~)			
Measuring range temp. (type-dependent)	Temp   Temp_rH +40+140 °F (default setting), optionally configured via Thermokon USEapp			
Measuring range humidity (type-dependent)	<b>Temp_rH</b> 0100% rH non-condensing, optionally configured via Thermokon USEapp (enthalpy, absolute humidity, dew point)			
Measuring range CO2	02000 ppm (default), 05000 ppm (optionally configured via Thermokon USEapp)			
Accuracy temperature (type-dependent)	Temp   Temp_rH ±0,5 K (typ. at 70 °F)			
Accuracy humidity (type-dependent)	Temp_rH ±2% between 1090% rH (typ. at 70 °F)			
Accuracy CO2	±50 ppm +3% of reading (typ. at 70 °F, 50% rH)			
Calibration	self-calibration, Dual Channel			
Sensor	CO2 NDIR (non-dispersiv, infrared)	VOC VOC sensor (heated metal oxide semiconductor)		
Display (optional)	LCD LCD 1.14x1.38 in. with RGB backlight			
Enclosure (type-dependent)	enclosure USE-M, PC, pure white, with removable cable entry	LCD cover PC, transparent		
Protection	IP65 according to EN 60529			
Cable entry	M25, for wire max. Ø=0.28 in., seal insert for fourfold cable entry			
Pipe (type-dependent)	CO2+VOC PA6, black, Ø=0.77 in., length 6 in.	<b>Temp   Temp_rH</b> PA6, black, Ø=0.77 in., length 7.1 in.		
	<b>Type 100</b> Length 2.7 in.	Type 100 Length 3.9 in.		
Connection electrical	Mainboard removable plug-in terminal, max. 14 AWG	Plug-in card removable plug-in terminal, max. 16 AWG		
Ambient condition	+32+122 °F, max. 85% rH short term condensation			
Notes	mixed gas sensors detect gases and vapours which can be oxidised (burnt): Body odours, tobacco smoke, exhalations emitted by materials (furniture, carpets, paint, glue)			

When several BUS devices are supplied by one 24 V AC voltage supply, it is to be ensured that all "positive" operating voltage input terminals (+) of the field devices are connected with each other and all "negative" operating voltage input terminals (-) (=reference potential) are connected together (in-phase connection of field devices). In case of reversed polarity at one field device, a supply voltage short-circuit would be caused by that device. The consequential short-circuit current flowing through this field my cause damage to it.


Therefore, pay attention to correct wiring.

Issue date: 8/4/2020 Page 5 / 6

# » CONNECTION PLAN

To change the output voltage range (default: 0..10 V to 0..5 V) via jumper, the display must be removed from the board first.

#### LK+ CO2+VOC (Temp\_rH) (LCD) RS485



The BACnet address of the device is set binary coded in the range of 1 ... 127 via 7 dip-switches. (the address 0 is reserved and cannot be selected).




## **BACnet Objects:**

USE-RS485 BACnet interface

A detailed description of the BACnet interface can be found in our downloadcenter:

→ Download

#### Address block 1



# Measuring values

Object	Access	Description	Unit
Al-1	R	relative humidity	%rF
AI-5	R	CO2	ppm
AI-6	R	VOC	%
AI-7	R	CO2 VOC Mix	%

#### Object AV-38 = 1 (Unit SI)


Objects	Access	Description		Unit
AI-0	R	temperature	SI	°C
AI-2	R	absolute humidity	SI	g/m³
AI-3	R	enthalpy	SI	KJ/kg
Ai-4	R	dew point	SI	°C

Page 6 / 6 Issue date: 8/4/2020

# Object AV-38 = 2 (Unit Imperial)

Objects	Access	Description		Unit
AI-0	R	temperature	Imperial	°F
AI-2	R	absolute humidity	Imperial	gr/ft³
AI-3	R	enthalpy	Imperial	BTU/lb
Ai-4	R	dew point	Imperial	°F

# » DIMENSIONS (IN.)



# » ACCESSORIES (INCLUDED IN DELIVERY)

Mounting base Item No. 631228 Mounting kit universal Item No. 698511

• Cover screw + screw cover• 2 Rawlplugs • 2 Screws (countersunk head) • 2 Screws (rounded head)

# » ACCESSORIES (OPTIONAL)

Bluetooth dongle

Item No. 668262

Filter stainless steel, wire mesh

Item No. 231169