

Communicative rotary actuator for zone valves

- Torque motor 1 Nm
- Nominal voltage AC/DC 24 V
- Control communicative
- Snap-assembly of the actuator
- Flow setting variable
- Communication via Belimo MP-Bus



Technical data

-	lectri	~		212
	CLUI	La	u	ala

Nominal voltage	AC/DC 24 V	
Nominal voltage frequency	50/60 Hz	
Nominal voltage range	AC 19.228.8 V / DC 21.628.8 V	
Power consumption in operation	0.6 W	
Power consumption in rest position	0.4 W	
Power consumption for wire sizing	1.1 VA	
Connection supply / control	Cable 1 m, 3 x 0.75 mm ²	
Parallel operation	Yes (note the performance data)	

Functional data

Torque motor	1 Nm	
Communicative control	MP-Bus	
Manual override	with actuator (clicked out)	
Running time motor	75 s / 90°	
Sound power level, motor	35 dB(A)	
Position indication	Mechanical	
Flow setting	see product features	

Safety data

Protection class IEC/EN	III Safety Extra-Low Voltage (SELV)		
Degree of protection IEC/EN	IP40		
EMC	CE according to 2014/30/EU		
Certification IEC/EN	IEC/EN 60730-1 and IEC/EN 60730-2-14		
Mode of operation	Type 1		
Rated impulse voltage supply / control	0.8 kV		
Control pollution degree	2		
Ambient temperature	540°C		
Storage temperature	-4080°C		
Ambient humidity	Max. 95% r.H., non-condensing		
Servicing	maintenance-free		
Weight	0.21 kg		



Weight

- This device has been designed for use in stationary heating, ventilation and air-conditioning systems
 and must not be used outside the specified field of application, especially in aircraft or in any other
 airborne means of transport.
- Outdoor application: only possible in case that no (sea) water, snow, ice, insolation or aggressive gases interfere directly with the device and that it is ensured that the ambient conditions remain within the thresholds according to the data sheet at any time.
- Only authorised specialists may carry out installation. All applicable legal or institutional installation regulations must be complied during installation.
- The device may only be opened at the manufacturer's site. It does not contain any parts that can be replaced or repaired by the user.
- Cables must not be removed from the device.

Safety notes



 The device contains electrical and electronic components and must not be disposed of as household refuse. All locally valid regulations and requirements must be observed.

Product features

Mode of operation

The actuator receives its digital positioning signal from the higher level controller via the MP-Bus and drives to the position defined. Connection MP serves as communication interface and does not supply an analogue measuring voltage.

Note: Neither a conventional operation with a standard signal nor a parametrisation of signals (e.g. running time) is possible. With the parametrisation devices a functional check can be executed and the MP address can be assigned.

When controlling CQ(K) actuators, it must be ensured that via MP-Bus, the setpoint steps are specified in whole percentages.

Simple direct mounting

Tool-free snap assembly.

The actuator can be plugged on the valve by hand (Caution! Just vertical movements). Pins must match the holes on the flange.

The mounting orientation in relation to the valve can be selected in 180° increments. (Possible two times)

Manual override

Click out the actuator and rotate the valve stem with the help of the actuator.

Adjustable angle of rotation

The angle of rotation of the actuator can be changed by clip in 2.5° increments. This is used to set the maximum flow rate of the valve.

High functional reliability

The actuator is overload protected, requires no limit switches and automatically stops when the end stop is reached.

Flow setting


Adjustable kv-values (C2..Q-.., C4..Q-..) are given in the respective zone valve data sheets.

2-way valve: Remove end stop clip and place at desired position.

3-way valve: Remove end stop clip (change-over application).

6-way valve: Remove end stop clip (cooling and heating application).

After every change of the flow setting by means of end stop clip, an adaptation must be triggered on the modulating actuators.



Accessories

Description	Туре
Gateway MP zu BACnet MS/TP	UK24BAC
Gateway MP to Modbus RTU	UK24MOD
Description	Туре
	EXT-WR-FP20-MP
Connection cable 5 m, A: RJ11 6/4 ZTH EU, B: free wire end for connection to MP/PP terminal	ZK2-GEN
MP-Bus power supply for MP actuators	ZN230-24MP
Description	Туре
Spindle extension CQ	ZCQ-E
Housing cover CQ, Colour: RAL-white	ZCQ-W
Description	Туре
Adapter for Service-Tool ZTH	MFT-C
Belimo PC-Tool, Software for adjustments and diagnostics	MFT-P
Service Tool, with ZIP-USB function, for parametrisable and communicative Belimo actuators, VAV controller and HVAC performance devices	ZTH EU
	Gateway MP zu BACnet MS/TP Gateway MP to Modbus RTU Description Connection cable 5 m, A: RJ11 6/4 ZTH EU, B: free wire end for connection to MP/PP terminal MP-Bus power supply for MP actuators Description Spindle extension CQ Housing cover CQ, Colour: RAL-white Description Adapter for Service-Tool ZTH Belimo PC-Tool, Software for adjustments and diagnostics Service Tool, with ZIP-USB function, for parametrisable and communicative




Electrical installation



Supply from isolating transformer.

Parallel connection of other actuators possible. Observe the performance data.

Wiring diagrams



Cable colours:

1 = black


2 = red

5 = orange


Functions

Functions when operated on MP-Bus

Connection on the MP-Bus




A) more actuators (max. 8)



There are no restrictions for the network topology (star, ring, tree or mixed forms are permitted). Supply and communication in one and the same 3-wire cable

- no shielding or twisting necessary
- no terminating resistors required

Operating controls and indicators



1 Push-button and LED display yellow

On: Angle of rotation adaptation active

Press button: Triggers angle of rotation adaptation, followed by standard mode

2 Push-button and LED display green

Off: No power supply or no MP-Bus level

Flickering: MP communication active

On: Power supply and MP-Bus level OK

Flashing: Depiction of MP address (Command from MP master)

- continuous: No MP address set

- with breaks: Pulse in accordance with MP address (e.g. 5 = MP5)

Press button: Confirmation of the addressing

Installation notes

Servicing Ball valves and rotary actuators are maintenance-free.

Before any service work on the final controlling device is carried out, it is essential to isolate the rotary actuator from the power supply (by unplugging the electrical cable if necessary). Any pumps in the part of



the piping system concerned must also be switched off and the appropriate slide valves closed (allow all components to cool down first if necessary and always reduce the system pressure to ambient pressure level).

The system must not be returned to service until the ball valve and the rotary actuator have been correctly reassembled in accordance with the instructions and the pipeline has been refilled by professionally trained personnel.

Service

Service Tools connection


The actuator can be parametrised by ZTH EU via terminal connection.

For extended parametrisation the PC tool can be connected.



Dimensions

Dimensional drawings



Further documentation

- Overview MP Cooperation Partners
- Tool connections
- Introduction to MP-Bus Technology
- The complete product range for water applications
- Data sheet for zone valves
- Installation instructions for zone valves and actuators
- General notes for project planning